

It is therefore possible to choose the parameters such that d is maximized, providing maximum spectral purity clearance about the desired frequency $sq+r$.

Figure 8. shows an embodiment of the rational synthesizer with a PLL using six way commutator with a non-square wave pattern, designed specifically to offer better second order spectral purity. It also incorporates a differential DSB mixer for applications requiring high frequency mixing and further incorporates a differential phase detector PD which permits the propagation of the symmetry into the differential low pass filter.

10 What is claimed is:

1. A method for rational digital synthesis comprising the steps of
providing a periodic pattern signals
feeding said periodic pattern signals to an N way commutator
clocking the periodic pattern generator at a frequency f_1 ; and
crotating the commutator at a frequency f_2 , thereby obtaining an output frequency
of $f_1 \pm f_2$.